

devoLO

Home Control Central Unit



first steps

Thank you for placing your trust in this devolo product.

Carefully read all instructions before setting up the device and store the instructions for later reference.

Icons



Very important note. Failure to observe this note may result in damage.



Important note that should be observed.



Background information and configuration tips for your device.

Intended use

Use the Home Control Central Unit as described in these instructions and in the Home Control online help to prevent damage and injuries.

CE conformity



When used as intended, the product conforms to the basic requirements of the directives 2014/53/EU, 2014/35/EU and the other relevant provisions of the Radio and Telecommunications Terminal Equipment Act (FTEG) and is designed for use in the EU, Switzerland and Norway. A printout of the CE declaration is included.

Safety instructions

For safety instructions, please refer to the chapter **Safety notes** on page 8.

devolo Home Control

Home Control (also known as home automation) refers to the specific control of electrically operated indoor household devices. The Home Control system by devolo uses the Z-Wave™ wireless standard.



- i** *For more information on the control and configuration of all devolo Home Control devices, as well as application examples, please refer to the Home Control online help.*

The Home Control Central Unit

The Home Control Central Unit is the heart of the devolo Home Control system. It is equipped with a user interface, called the **Home Control portal**, which is used to coordinate all of your Home Control devices. Access to the Home Control portal is very easy both from the **my devolo app** and at **www.mydevolo.com** in a browser.

While the my devolo app lets you operate and control your Home Control devices easily and conveniently, access to the **Home Control portal** in your browser at **www.mydevolo.com** provides you with the **complete range of Home Control functions and benefits**. You can use this to carry out **initial** and **administrative actions** such as **initial registration** of the Home Control Central Unit or **teaching in** (including) and **configuring** Home Control devices.



The device is designed for indoor use only.

The Home Control Central Unit provides a button for dLAN encryption (home icon), a Home Control button (check mark), a network (LAN) and a USB connection. The USB connection is provided for future applications and is not active at this time.

Figure is country-specific



Basic guidelines for setting up a Home Control network

When planning your Home Control network, consider the optimal placement of all devices with regard to the wireless range so as to best avoid weak signals and interference sources. Drawing up a sketch may help you to determine the desired locations of all your devices.

- i** *Weak signals due to attenuation can result from furniture, plants and especially metal objects which are located between the devices. Possible sources of interference include electrical devices such as a microwave or computer. In such instances, keep your device at least around 50 cm (19 in) away from the source.*

Connecting the Home Control Central Unit

- ① Taking the above factors into consideration, plug the Home Control Central Unit into a wall outlet that is located centrally in your house or flat.
- ② **Connecting the Home Control Central Unit to the Internet router**
 - a) To connect the Home Control Central Unit to the **Internet router** via your **existing dLAN network**, **first** press the **home** or **encryption button** (for 1 second) on an **existing dLAN adapter** (e.g. the one on the Internet router) in your network, and **then** – within 2 minutes – press the **dLAN encryption button** with the home icon (for 1 second) on the **Home Control** Central Unit.

or

- b) To connect the Home Control Central Unit to the **LAN directly** at your **Internet router**, plug the **included network cable** into **both devices**.
- ③ As soon as you are **connected** to your **dLAN** or **LAN** network, the Home Control button (check mark) on the device **illuminates white**.



For the Home Control Central Unit to be recognised automatically in the Home Control portal when first installed, both the Home Control Central Unit and the device with which you are accessing it must be connected through the same LAN. If instead you use separate Internet connections, you have to enter the serial number of the Home Control Central Unit manually. The serial number (e.g. S/N: 12312312312312) of the Home Control Central Unit is located on the title page of the installation guide and on the label on the rear of the unit's housing. If you have

to enter the serial number, you should do so when you add the Home Control Central Unit in the portal, as described under instruction ⑨.

Registering the Home Control Central Unit for the first time

- ④ To register the Home Control Central Unit for the first time, use your **PC or laptop**. In your browser, go to **www.mydevolo.com**.
- ⑤ Select **Create an account** to register a new account.
- ⑥ After you have confirmed your data by clicking **Apply**, you will receive a registration message at the e-mail address you indicated while creating your account. Click the link **Finish registration**, after which you will receive an activation confirmation.
- ⑦ Click the **my devolo** link to return to the login page, where you can now use your existing user name and password to log in.
- ⑧ On the dashboard page, select **Home Control**.
- ⑨ There, add your Home Control Central Unit by clicking the **plus** button. Confirm your input with **Apply** and follow the instructions in the Home Control portal.

i *From now on, you can take electronic control conveniently using the Home Control portal of the Home Control Central Unit. For more information on time control and configuration, as well as application examples, please refer to the Home Control online help.*

Safety notes

It is essential to have read and understood all safety and operating instructions before the devolo device is used for the first time; keep them safe for future reference.



DANGER due to electricity

Users should never open devolo devices. **Opening the device poses a risk of electric shock!**

Users do not need to carry out any maintenance on devolo devices. In the event of damage, disconnect the devolo device from the mains supply by pulling it or its plug out of the power outlet. Then contact qualified specialist personnel (after-sales service) exclusively. Damage is deemed to have occurred, for example,

- if the power plug is damaged
- if the devolo device has been showered with liquid (e.g. rain or water).
- if the devolo device is inoperable.
- if the housing of the devolo device is damaged.

devolo devices may only be operated using a mains power supply, as described on the nameplate.

To disconnect the devolo device from the mains supply, pull the device itself or its mains plug from the power outlet. The power outlet and all connected network devices should be easily accessible so that you can pull the mains plug quickly if needed.

Only use the devolo device indoors and at a dry location.

Disconnect the devolo device from the mains supply to clean! Avoid solvent cleaning agents since they can cause damage to the housing. Only use a dry towel for cleaning.



DANGER due to overheating

Multiple devolo devices must not be interlocked.

devolo devices should only be installed at locations that guarantee adequate ventilation. Slots and openings on the housing are used for ventilation:

- Do not cover devolo devices when they are operating.
- Do not place any objects on devolo devices.
- Do not insert any objects into the openings of devolo devices.
- devolo devices must not be placed directly next to an open flame (such as fire or candles).
- devolo devices must not be exposed to direct heat radiation (e.g. radiator, direct sunlight).

It is normal for the housing to get a little warm when the device is plugged in.

Service and warranty

Warranty: 3 years

If your devolo device is found to be defective during initial installation or within the warranty period, please contact the vendor who sold you the product. The vendor will take care of the repair or warranty claim for you. The complete warranty conditions can be found at www.devolo.com/warranty.

Great Britain	+44 203 0241 838 *	support@devolo.co.uk
Portugal	+351 707 200 896 *	support@devolo.pt
Spain	+34 902 887 682 *	support@devolo.es
Sweden	+46 771 400 480 *	support@devolo.se
Other countries	+49 241 70 525 18 *	support@devolo.com

* Detailed information about the actual costs of the telephone calls can be found on the devolo website.

Disposal

The Home Control Central Unit must not be disposed of with the household waste. Instead, you can return these at no charge at your municipal collection point or at the retailer (e. g. supermarket, specialist shop).



devolo

devolo AG

Charlottenburger Allee 60

52068 Aachen – Germany

www.devolo.com

44453/0716